



## Thuraya WE

Your remote WiFi hotspot.

### This is Thuraya WE







Empowering you to get out of your comfort zone, with the comfort of knowing that you can stay connected. Designed with your personal endeavors in mind, the Thuraya WE is the world's first dual-mode hotspot, allowing you to switch modes between Satellite & LTE with just the click of a button. Even more, the Thuraya WE can transform any area into a WiFi hotspot, allowing you to connect 10 smart devices within a 30m radius – ideal for when you're setting up camp or conducting personal business abroad.

When your cross-country travels frequently go beyond the reach of terrestrial communications, the

Thuraya WE ensures you can move in and out of these areas with ease, by extending your data coverage. The Thuraya WE app allows you to transform any of your smart devices into a satellite phone, keeping you in touch with the world via calls, messages, emails and so much more. Offering protection from dust and water spray, this light-weight satellite terminal is the ideal companion

for all your rural travels and business ventures.

### Product Features

- 
**Single SIM, dual mode hotspot**  
 The only hotspot in the market offering dual-mode capability. It extends data coverage by offering Satellite & LTE broadband data services allowing you to move in and out of terrestrial coverage areas with ease.
- 
**Manual or auto-network selection**  
 Flexibly switch between networks by setting up the auto-network switching function on the web interface or smartphone app. The hotspot will automatically switch from your default network to the other network once you're out of coverage.
- 
**Calls and text messages in Satellite Mode**  
 The Thuraya WE app transforms your smart device into a satellite phone, it enables you to access your existing phone's contact list to make satellite calls and SMS's when satellite mode is selected.
- 
**Easy to use interface**  
 To fully control the hotspot, Thuraya has developed a user-friendly interface that can be accessed either through the web or through a mobile app compatible with iOS and Android systems.
- 
**Unified communications**  
 Transform any area into a Wi-Fi hotspot, connect all your devices and applications, and enjoy the internet by connecting up to 10 smart devices to the Thuraya WE Wi-Fi hotspot, within a radius of 30 meters or more.
- 
**Lightweight and durable**  
 Weighing 1 kg only, Thuraya WE is compact light, and portable. It holds the globally recognized Ingress Protection Rating IP54 which provides protection from dust & water spray to withstand harsh environments.



Frequently on the move, and always connected.

## Product Specifications

POWER SPECIFICATIONS	
Rated Input	12V DC, 3A max, 12V ±0.6V
Battery Type	Lithium Ion, rechargeable
Battery Capacity	7.4V, 6Ah, (2S2P)
Min Charge cycles	300, At 75% Depth of Discharge (DoD)
RUN TIMES (BATTERY)	
GSM – standby	20hrs
GSM – Data	9hrs
Sat – standby	6hrs
Sat – voice	5hrs
Sat – Data	3 hrs
PHYSICAL	
Weight	1.00Kg
Size	230mm x 197mm x 24mm
DC input Connector	2.5mm ID / 5.5 OD Jack, Centre Positive.
SIM Port	Mini
ENVIRONMENTAL	
Operating Temperature	-20°C to +55°C, Device ambient Temp.
Transport Temperature	-20°C to +60°C, With Battery
Storage Temperature	-20°C to +60°C, With Battery
Battery Charging Temperature	0°C to +45°C, Battery Cell Temp.
Humidity	5% to 95% RH, At a temperature of 40°C
Ingress protection	IP54 compliant
SATELLITE SERVICES	
Voice calls	Circuit Switch
Data	Up to 384Kbps on standard mode
SMS	Voice mode only

CELLULAR SERVICES	
Data	3G / LTE
SMS	3G / LTE
Wi-Fi	
Range	30+ meters Clear line of sight
Number of clients	Up to 10 users
Security	WPA2 Personal Authentication
GNSS SUPPORTED SYSTEMS	
GPS, Glonass, Beidou	
ROUTER FEATURES	
Firewall, Mac Filtering, DMZ, NAT, Port Forwarding	
NATIVE CLIENT APPLICATIONS	
Android	Minimum version 4.2 (API17), Integrated Phonebook
iOS	Minimum version iOS9, Integrated Phonebook
Published API	For 3 <sup>rd</sup> Party client application development
AC CHARGER	
Output	12.0V +5% 36W
Operating Temperature	0°C to 40°C
Efficiency Level	VI
TRANSMISSION FREQUENCIES	
Satellite	Tx 1626.5-1660.5 Mhz, (earth to space) Rx 1525-1559 Mhz, (space to earth)
4G LTE	Band 20 (800 MHz), Band 5 (850 MHz), Band 8 (900 MHz), Band 3 (1800 MHz), Band 1 (2100 MHz), Band 7 (2600 MHz)
3G	Band 5 (850 MHz), Band 2 (1900MHz)
Wi-Fi	Type G, 2.4GHz band IEEE 802.11 b/g/n module
REGULATORY & APPROVALS	
FCC, CE, Safety IEC 60950 & CB certificate, ITU, RCM, REACH, RoHS, IP54	

+971 (4) 435 6800  
info@cygnus.co | www.cygnus.co



**THURAYA**  
SPACE42